

PRAKTISCH | Talking Automatic Digital Blood Pressure Monitor

This new digital blood pressure monitor is an automatic measuring device to be used on the upper arm. It enables simple, accurate and fast measurement of blood pressure and pulse rate by use of the oscillometric method and people-orientated design.

- | | |
|-------------------------------|--------------------------------------|
| ❶ Big LCD screen | ❷ Irregular Heartbeat Detector (IHB) |
| ❸ 120 Memories | ❸ Average of last 3 readings |
| ❹ 2 languages chooseable | ❹ Low battery indicator |
| ❺ Date and time display | ❺ Auto power off |
| ❻ Motion detection | |
| ❼ Hypertension risk indicator | |

Technical Specifications

Model	Praktisch
Display	LCD digital display
Measuring Range	Pressure: 0kPa~38.66kPa (0mmHg~290mmHg) Pulse: 40~180/min
Accuracy	Pressure: within ± 0.4 kPa (3mmHg) Pulse: within $\pm 5\%$ of the reading
Work Mode	Automatic inflation and measurement
Measuring Method	Oscillometric method
Power source	4X1.5V "AA"batteries or AC adapter DC6V
Operating Condition	Temperature: 5°C~40°C Humidity: 15%RH~85%RH Air Pressure: 860hPa~1060hPa
Storage Condition	Temperature: -20°C~70°C Humidity: 10%RH~95%RH Air Pressure: 860hPa~1060hPa
Weight	300g(without batteries)
Dimension	150 × 110mm × 70mm
Cuff	BF applied part
Cuff Circumference	22~42cm
Accessories	Arm cuff

